



1. Press the **TOOLS** button on the remote control to display the setup screen.

Configuration				
System Data Weezago Version 0.229 Network Connected (wired:1 wif Mac fc8f90d1e34e SUD KLCJ80TENI6R8 S/N OMTKHTW6000271H Store Data Server Host http://sssp.weezat Mac fc8f90d1e34e System Status Lamp Normal Temperature Normal Fan Normal Current temperature 57°C	:-1) go.com			
Back to Player 'RETURN'	REBOOT 'RED'	FIRMWARE 'BLUE'	TEST INTERNET '0'	

2. Press the **BLUE** (color) button to display the update screen.

FIRMWARE		
System Info		
Weezago #0.229 Network Connected (wired)	wifi:-1)	
• Mac fc8f90d1e34e		
Firmware Data		
Main FW : T-GFSLE5AKUC	ersion : 1005.0 ->1007.3	
• Model : DB10E	5 VEISION - 1005 -> 1005	
	!! Download time can be long !!	
	DB10E 1 T-GFSLEWWS3 -> 1009	
	DB10E 0 T-GFSLE5AKUC -> 1007.3	
	HIT ENTER to STRART UPDATE	

3. Press the ENTER key when a new firmware version is available.

NB : If no update is available the **ENTER** key restarts the screen.



4. The screen automatically restarts on the update page and downloads the necessary files.

NB : the download time varies depending on the speed of the Internet connection.

Mise à jour FIRMWARE
100%
DOWNLOAD FILE T-GFSLEWWS3.zip size : 26,78kB
MàJ maintenant
Mise à jour du logiciel produit Votre produit redémarrera automatiquement
après la mise à jour.
90%
Dernière vérif. MàJ : 22/10/2015 15:21

The update process will launch automatically after the complete download of the files.

NB: several consecutive updates can be repeated automatically.



If the screen does not restart automatically at the end of the update process and displays the setup menu, restart the screen using the remote control.

Mise à jour du l	Mise à jour du logiciel		Mettez le logiciel à jour en téléchargeant les fichiers de mise à jour.
MàJ maintenant Mise à iour auto	Arrêt	Version actuelle : 1005	